

Performance You Can Hear


The Mogan Elite Omni Earset Microphone delivers full-frequency vocal reproduction for broadcast, theater, and presentation. Featuring a discreet, 2.5 mm Omni-directional condenser element, it captures every vocal nuance in sparkling detail. A fully adjustable boom and earpiece enables precise positioning for maximum stability and comfort. The Elite earset is ideal for both spoken word and vocal performance.

Model	Color	Connector	SKU
Elite Earset	Beige	AKG	EXO-BG-AK
Elite Earset	Beige	Audio-Technica	EXO-BG-AT
Elite Earset	Beige	Sennheiser	EXO-BG-SE
Elite Earset	Beige	Shure	EXO-BG-SH
Elite Earset	Black	AKG	EXO-BK-AK
Elite Earset	Black	Audio-Technica	EXO-BK-AT
Elite Earset	Black	Sennheiser	EXO-BK-SE
Elite Earset	Black	Shure	EXO-BK-SH

Kit Contains:

Earset microphone 4 ft reinforced cable Foam windscreens Single-cable clip Aluminium case

Capsule	Back-electret condenser	
Polar Pattern	Omni-directional	
Frequency Response	20 Hz to 20 kHz	
Sensitivity	-45 ± 3 dB re 1 V/Pa	
Equivalent Noise Level	28 dB (A-weighted)	
Signal-to-Noise Ratio	66 dB	
Output Impedance	$4.5 \text{ K} \Omega \pm 30\%$	
Maximum SPL	140 dB	
Operating Current	<100 mA	
Power Requirement	0.9 VDC (opt), 5 VDC (max)	
Overall Length	135 mm	
Boom Length	90 mm	
Capsule Diameter	2.5 mm	
Connector Type	Compact-screw	
Cable Diameter/Length	1.4 mm x 1.2 m	
Weight	13 g	



Connectivity

Mogan's interchangeable cable system enables one to connect a single microphone to multiple wireless transmitters. Each microphone includes a cable with a hardwired connector for Shure, AKG, Sennheiser, or Audio-Technica. These cables are also available for special order.

Limited Warranty

Mogan Microphones are warranted to be free of defects in materials and workmanship for one year. Visit **www.moganmicrophones.com** for details.



